

ELECTRONIC PORTABLE APPLIANCEBACKGROUND OF THE INVENTION

The present invention relates to electronic portable appliances to be driven on generation power of a power generating means or the like and, more particularly, to an electronic portable appliance provided with a power feed means having a power generating means or a generating means and booster circuit to increase the voltage of the power generating means, a power storing means to store power supplied by the power feed means, and a drive circuit driven on power supplied by the power feed means or on storage power of the power storing means, for use in a wrist watch driven on power supplied from a thermoelectric conversion device, solar battery or the like.

There is shown in Fig. 6 a schematic block diagram of an electronic portable appliance according to a related art. In Fig. 6, an electronic portable appliance 600 is configured by a power feed means 10 for supplying electric power, a power storing means 40 for storing power supplied by the power feed means 10 through a diode element 601, and a drive circuit 50 to be driven on power supplied by the power feed means 10 through the same diode 601 or on storage power built up on the power storing means 40. Furthermore, the power feed means 10 is formed by a power generating means, a booster circuit for increasing the voltage of the power generating means and so on.

In such an electronic portable appliance, the power feed

10/20/99
JCS44 U.S. PRORECEIVED
OCT 20 1999
FBISWB
A1

Sub
A-10

means 10 is also required to be reduced in size and weight due to the reductions of size and weight of the appliance. Due to this, there is a tendency toward decreasing the power supplied by the power feed means 10. On the other hand, there has become desired to improve the charge efficiency to the power storing means 40 and effectively utilize the power stored on the storage means 50, due to a desire for increasing the operating time of the electronic portable appliance.

Accordingly, to realize the further reduction in size and weight or further increase in operation time for the electronic portable appliance, it is indispensable to further increase the charge efficiency to the power storing means and effectively utilize the storage power on the power storing means.

Sub
A-11

In the related art electronic portable appliance, rectification is made by the diode element 601 in order to prevent the stored power from reversely flowing in the event that the generation power run out. However, the major cause of lowering the charge efficiency lies in loss due to forward drop voltage across the diode element 601. Accordingly, the use of a diode element with a low forward drop voltage improves the charge efficiency. Meanwhile, the major cause of preventing effective utilization of the power stored on the power storing means 40 is current loss due to reverse current through the diode element 601. That is, it is satisfactory to use such a diode element that is low in forward drop voltage but less in reverse current. However, for the diode element, decrease in forward drop voltage and

sub
P22

reduction in reverse current are in a relationship of trade off. That is, there has been a problem that it is impossible to realize an electronic portable appliance smaller in size and lighter in weight and operable over a longer time so long as a diode element is used in the above-stated portion.

SUMMARY OF THE INVENTION

It is therefore an object of the present invention to provide an electronic portable appliance which is improved in charge efficiency but reduced in useless power such as reverse current, in order to realize reduction of size and weight and longer time operation of the apparatus.

sub
P23

An electronic portable appliance of the present invention to be driven on generation power, is configured by a power feed means formed by only a power generating means or a combination of a power generation means and a booster means, a power storing means for storing power of the power feed means, a drive circuit to be operated on power of the power feed means or power stored on the power storing means, a switch means provided on a charging path for charging power of the power feed means to the power storing means to have a function of flowing a charge current and cutting off a reverse current and a feature of having a resistor component to produce a potential difference in the event a current flow, a voltage comparator circuit for comparing voltages on between a charging path point forward of the switch means and a charging path point backward of the switch means, and a control circuit for controlling the switch means depending on a result of

Sub H3
Sub H4
Sub H5
Sub H6
Sub H7
Sub H8
Sub H9
Sub H10
Sub H11
Sub H12
Sub H13
Sub H14
Sub H15
Sub H16
Sub H17
Sub H18
Sub H19
Sub H20
Sub H21
Sub H22
Sub H23
Sub H24
Sub H25
Sub H26
Sub H27
Sub H28
Sub H29
Sub H30
Sub H31
Sub H32
Sub H33
Sub H34
Sub H35
Sub H36
Sub H37
Sub H38
Sub H39
Sub H40
Sub H41
Sub H42
Sub H43
Sub H44
Sub H45
Sub H46
Sub H47
Sub H48
Sub H49
Sub H50
Sub H51
Sub H52
Sub H53
Sub H54
Sub H55
Sub H56
Sub H57
Sub H58
Sub H59
Sub H60
Sub H61
Sub H62
Sub H63
Sub H64
Sub H65
Sub H66
Sub H67
Sub H68
Sub H69
Sub H70
Sub H71
Sub H72
Sub H73
Sub H74
Sub H75
Sub H76
Sub H77
Sub H78
Sub H79
Sub H80
Sub H81
Sub H82
Sub H83
Sub H84
Sub H85
Sub H86
Sub H87
Sub H88
Sub H89
Sub H90
Sub H91
Sub H92
Sub H93
Sub H94
Sub H95
Sub H96
Sub H97
Sub H98
Sub H99
Sub H100
Sub H101
Sub H102
Sub H103
Sub H104
Sub H105
Sub H106
Sub H107
Sub H108
Sub H109
Sub H110
Sub H111
Sub H112
Sub H113
Sub H114
Sub H115
Sub H116
Sub H117
Sub H118
Sub H119
Sub H120
Sub H121
Sub H122
Sub H123
Sub H124
Sub H125
Sub H126
Sub H127
Sub H128
Sub H129
Sub H130
Sub H131
Sub H132
Sub H133
Sub H134
Sub H135
Sub H136
Sub H137
Sub H138
Sub H139
Sub H140
Sub H141
Sub H142
Sub H143
Sub H144
Sub H145
Sub H146
Sub H147
Sub H148
Sub H149
Sub H150
Sub H151
Sub H152
Sub H153
Sub H154
Sub H155
Sub H156
Sub H157
Sub H158
Sub H159
Sub H160
Sub H161
Sub H162
Sub H163
Sub H164
Sub H165
Sub H166
Sub H167
Sub H168
Sub H169
Sub H170
Sub H171
Sub H172
Sub H173
Sub H174
Sub H175
Sub H176
Sub H177
Sub H178
Sub H179
Sub H180
Sub H181
Sub H182
Sub H183
Sub H184
Sub H185
Sub H186
Sub H187
Sub H188
Sub H189
Sub H190
Sub H191
Sub H192
Sub H193
Sub H194
Sub H195
Sub H196
Sub H197
Sub H198
Sub H199
Sub H200
Sub H201
Sub H202
Sub H203
Sub H204
Sub H205
Sub H206
Sub H207
Sub H208
Sub H209
Sub H210
Sub H211
Sub H212
Sub H213
Sub H214
Sub H215
Sub H216
Sub H217
Sub H218
Sub H219
Sub H220
Sub H221
Sub H222
Sub H223
Sub H224
Sub H225
Sub H226
Sub H227
Sub H228
Sub H229
Sub H230
Sub H231
Sub H232
Sub H233
Sub H234
Sub H235
Sub H236
Sub H237
Sub H238
Sub H239
Sub H240
Sub H241
Sub H242
Sub H243
Sub H244
Sub H245
Sub H246
Sub H247
Sub H248
Sub H249
Sub H250
Sub H251
Sub H252
Sub H253
Sub H254
Sub H255
Sub H256
Sub H257
Sub H258
Sub H259
Sub H260
Sub H261
Sub H262
Sub H263
Sub H264
Sub H265
Sub H266
Sub H267
Sub H268
Sub H269
Sub H270
Sub H271
Sub H272
Sub H273
Sub H274
Sub H275
Sub H276
Sub H277
Sub H278
Sub H279
Sub H280
Sub H281
Sub H282
Sub H283
Sub H284
Sub H285
Sub H286
Sub H287
Sub H288
Sub H289
Sub H290
Sub H291
Sub H292
Sub H293
Sub H294
Sub H295
Sub H296
Sub H297
Sub H298
Sub H299
Sub H300
Sub H301
Sub H302
Sub H303
Sub H304
Sub H305
Sub H306
Sub H307
Sub H308
Sub H309
Sub H310
Sub H311
Sub H312
Sub H313
Sub H314
Sub H315
Sub H316
Sub H317
Sub H318
Sub H319
Sub H320
Sub H321
Sub H322
Sub H323
Sub H324
Sub H325
Sub H326
Sub H327
Sub H328
Sub H329
Sub H330
Sub H331
Sub H332
Sub H333
Sub H334
Sub H335
Sub H336
Sub H337
Sub H338
Sub H339
Sub H340
Sub H341
Sub H342
Sub H343
Sub H344
Sub H345
Sub H346
Sub H347
Sub H348
Sub H349
Sub H350
Sub H351
Sub H352
Sub H353
Sub H354
Sub H355
Sub H356
Sub H357
Sub H358
Sub H359
Sub H360
Sub H361
Sub H362
Sub H363
Sub H364
Sub H365
Sub H366
Sub H367
Sub H368
Sub H369
Sub H370
Sub H371
Sub H372
Sub H373
Sub H374
Sub H375
Sub H376
Sub H377
Sub H378
Sub H379
Sub H380
Sub H381
Sub H382
Sub H383
Sub H384
Sub H385
Sub H386
Sub H387
Sub H388
Sub H389
Sub H390
Sub H391
Sub H392
Sub H393
Sub H394
Sub H395
Sub H396
Sub H397
Sub H398
Sub H399
Sub H400
Sub H401
Sub H402
Sub H403
Sub H404
Sub H405
Sub H406
Sub H407
Sub H408
Sub H409
Sub H410
Sub H411
Sub H412
Sub H413
Sub H414
Sub H415
Sub H416
Sub H417
Sub H418
Sub H419
Sub H420
Sub H421
Sub H422
Sub H423
Sub H424
Sub H425
Sub H426
Sub H427
Sub H428
Sub H429
Sub H430
Sub H431
Sub H432
Sub H433
Sub H434
Sub H435
Sub H436
Sub H437
Sub H438
Sub H439
Sub H440
Sub H441
Sub H442
Sub H443
Sub H444
Sub H445
Sub H446
Sub H447
Sub H448
Sub H449
Sub H450
Sub H451
Sub H452
Sub H453
Sub H454
Sub H455
Sub H456
Sub H457
Sub H458
Sub H459
Sub H460
Sub H461
Sub H462
Sub H463
Sub H464
Sub H465
Sub H466
Sub H467
Sub H468
Sub H469
Sub H470
Sub H471
Sub H472
Sub H473
Sub H474
Sub H475
Sub H476
Sub H477
Sub H478
Sub H479
Sub H480
Sub H481
Sub H482
Sub H483
Sub H484
Sub H485
Sub H486
Sub H487
Sub H488
Sub H489
Sub H490
Sub H491
Sub H492
Sub H493
Sub H494
Sub H495
Sub H496
Sub H497
Sub H498
Sub H499
Sub H500
Sub H501
Sub H502
Sub H503
Sub H504
Sub H505
Sub H506
Sub H507
Sub H508
Sub H509
Sub H510
Sub H511
Sub H512
Sub H513
Sub H514
Sub H515
Sub H516
Sub H517
Sub H518
Sub H519
Sub H520
Sub H521
Sub H522
Sub H523
Sub H524
Sub H525
Sub H526
Sub H527
Sub H528
Sub H529
Sub H530
Sub H531
Sub H532
Sub H533
Sub H534
Sub H535
Sub H536
Sub H537
Sub H538
Sub H539
Sub H540
Sub H541
Sub H542
Sub H543
Sub H544
Sub H545
Sub H546
Sub H547
Sub H548
Sub H549
Sub H550
Sub H551
Sub H552
Sub H553
Sub H554
Sub H555
Sub H556
Sub H557
Sub H558
Sub H559
Sub H560
Sub H561
Sub H562
Sub H563
Sub H564
Sub H565
Sub H566
Sub H567
Sub H568
Sub H569
Sub H570
Sub H571
Sub H572
Sub H573
Sub H574
Sub H575
Sub H576
Sub H577
Sub H578
Sub H579
Sub H580
Sub H581
Sub H582
Sub H583
Sub H584
Sub H585
Sub H586
Sub H587
Sub H588
Sub H589
Sub H590
Sub H591
Sub H592
Sub H593
Sub H594
Sub H595
Sub H596
Sub H597
Sub H598
Sub H599
Sub H600
Sub H601
Sub H602
Sub H603
Sub H604
Sub H605
Sub H606
Sub H607
Sub H608
Sub H609
Sub H610
Sub H611
Sub H612
Sub H613
Sub H614
Sub H615
Sub H616
Sub H617
Sub H618
Sub H619
Sub H620
Sub H621
Sub H622
Sub H623
Sub H624
Sub H625
Sub H626
Sub H627
Sub H628
Sub H629
Sub H630
Sub H631
Sub H632
Sub H633
Sub H634
Sub H635
Sub H636
Sub H637
Sub H638
Sub H639
Sub H640
Sub H641
Sub H642
Sub H643
Sub H644
Sub H645
Sub H646
Sub H647
Sub H648
Sub H649
Sub H650
Sub H651
Sub H652
Sub H653
Sub H654
Sub H655
Sub H656
Sub H657
Sub H658
Sub H659
Sub H660
Sub H661
Sub H662
Sub H663
Sub H664
Sub H665
Sub H666
Sub H667
Sub H668
Sub H669
Sub H670
Sub H671
Sub H672
Sub H673
Sub H674
Sub H675
Sub H676
Sub H677
Sub H678
Sub H679
Sub H680
Sub H681
Sub H682
Sub H683
Sub H684
Sub H685
Sub H686
Sub H687
Sub H688
Sub H689
Sub H690
Sub H691
Sub H692
Sub H693
Sub H694
Sub H695
Sub H696
Sub H697
Sub H698
Sub H699
Sub H700
Sub H701
Sub H702
Sub H703
Sub H704
Sub H705
Sub H706
Sub H707
Sub H708
Sub H709
Sub H710
Sub H711
Sub H712
Sub H713
Sub H714
Sub H715
Sub H716
Sub H717
Sub H718
Sub H719
Sub H720
Sub H721
Sub H722
Sub H723
Sub H724
Sub H725
Sub H726
Sub H727
Sub H728
Sub H729
Sub H730
Sub H731
Sub H732
Sub H733
Sub H734
Sub H735
Sub H736
Sub H737
Sub H738
Sub H739
Sub H740
Sub H741
Sub H742
Sub H743
Sub H744
Sub H745
Sub H746
Sub H747
Sub H748
Sub H749
Sub H750
Sub H751
Sub H752
Sub H753
Sub H754
Sub H755
Sub H756
Sub H757
Sub H758
Sub H759
Sub H760
Sub H761
Sub H762
Sub H763
Sub H764
Sub H765
Sub H766
Sub H767
Sub H768
Sub H769
Sub H770
Sub H771
Sub H772
Sub H773
Sub H774
Sub H775
Sub H776
Sub H777
Sub H778
Sub H779
Sub H780
Sub H781
Sub H782
Sub H783
Sub H784
Sub H785
Sub H786
Sub H787
Sub H788
Sub H789
Sub H790
Sub H791
Sub H792
Sub H793
Sub H794
Sub H795
Sub H796
Sub H797
Sub H798
Sub H799
Sub H800
Sub H801
Sub H802
Sub H803
Sub H804
Sub H805
Sub H806
Sub H807
Sub H808
Sub H809
Sub H810
Sub H811
Sub H812
Sub H813
Sub H814
Sub H815
Sub H816
Sub H817
Sub H818
Sub H819
Sub H820
Sub H821
Sub H822
Sub H823
Sub H824
Sub H825
Sub H826
Sub H827
Sub H828
Sub H829
Sub H830
Sub H831
Sub H832
Sub H833
Sub H834
Sub H835
Sub H836
Sub H837
Sub H838
Sub H839
Sub H840
Sub H841
Sub H842
Sub H843
Sub H844
Sub H845
Sub H846
Sub H847
Sub H848
Sub H849
Sub H850
Sub H851
Sub H852
Sub H853
Sub H854
Sub H855
Sub H856
Sub H857
Sub H858
Sub H859
Sub H860
Sub H861
Sub H862
Sub H863
Sub H864
Sub H865
Sub H866
Sub H867
Sub H868
Sub H869
Sub H870
Sub H871
Sub H872
Sub H873
Sub H874
Sub H875
Sub H876
Sub H877
Sub H878
Sub H879
Sub H880
Sub H881
Sub H882
Sub H883
Sub H884
Sub H885
Sub H886
Sub H887
Sub H888
Sub H889
Sub H890
Sub H891
Sub H892
Sub H893
Sub H894
Sub H895
Sub H896
Sub H897
Sub H898
Sub H899
Sub H900
Sub H901
Sub H902
Sub H903
Sub H904
Sub H905
Sub H906
Sub H907
Sub H908
Sub H909
Sub H910
Sub H911
Sub H912
Sub H913
Sub H914
Sub H915
Sub H916
Sub H917
Sub H918
Sub H919
Sub H920
Sub H921
Sub H922
Sub H923
Sub H924
Sub H925
Sub H926
Sub H927
Sub H928
Sub H929
Sub H930
Sub H931
Sub H932
Sub H933
Sub H934
Sub H935
Sub H936
Sub H937
Sub H938
Sub H939
Sub H940
Sub H941
Sub H942
Sub H943
Sub H944
Sub H945
Sub H946
Sub H947
Sub H948
Sub H949
Sub H950
Sub H951
Sub H952
Sub H953
Sub H954
Sub H955
Sub H956
Sub H957
Sub H958
Sub H959
Sub H960
Sub H961
Sub H962
Sub H963
Sub H964
Sub H965
Sub H966
Sub H967
Sub H968
Sub H969
Sub H970
Sub H971
Sub H972
Sub H973
Sub H974
Sub H975
Sub H976
Sub H977
Sub H978
Sub H979
Sub H980
Sub H981
Sub H982
Sub H983
Sub H984
Sub H985
Sub H986
Sub H987
Sub H988
Sub H989
Sub H990
Sub H991
Sub H992
Sub H993
Sub H994
Sub H995
Sub H996
Sub H997
Sub H998
Sub H999
Sub H1000

As discussed before, the resistance component possessed by the switch means produces a potential difference at respective ends of the switch means during charging or current reverse flow. It is therefore possible to for the voltage comparator circuit in the control circuit to perform stable voltage comparison. Thus, realized is a control circuit capable of stably controlling the switch means.

Accordingly, the switch means and control circuit can realize an equivalent function to the diode element used in the conventional electronic portable appliance. In the case of large charge current, the switch means decreases the efficiency of charging to a degree corresponding to the resistance component due to voltage drop through the resistance component. Where the charge current is low, there is almost no decrease of charge current due to voltage drop through the resistance component. Moreover, reverse current is suppressed extremely low. Accordingly, where only a certain degree of charge current occur, it is possible to improve the charge efficiency and decrease the reverse current.

Furthermore, the invention in the above configuration is structured that the resistance component of the switch means is reduced in resistance value as low as possible. Instead, a resistor element is provided in series with the switch means so that a potential difference is produced during charging or reverse current flow by the resistor element.

Due to this, it is possible to set to produce an optimal

potential difference upon charging or reverse current flow, by changing the resistance element in accordance with the ability of the power feed means. Accordingly, labor and time can be omitted in designing an especial switch means having a resistance component with a resistance value meeting the ability of the power feed means or searching for a switch means having a close resistance component to the resistance value.

Sub 47
Furthermore, the invention in the above configuration is structured that a diode element is provided in series with the switch means in place of using the resistor element wherein the diode has a lower forward drop voltage than that of the diode used in the conventional electronic portable appliance.

Sub 47
Due to this, the diode element, in place of the resistor element, can produce a potential difference during charging or reverse current flow. Thus, realized is a control circuit to stably control the switch means, as discussed above. Moreover, because the usability of a lower forward drop voltage of a diode element than that of the diode element used in the conventional electronic portable appliance improves the charging efficiency. Moreover, the switch element can cut off reverse current, hence reducing the reverse current. Furthermore, for large charge current the diode element is lower in drop voltage in a charging direction as compared to the resistor element. In such a case, the charging efficiency increases as compared to the structure using the resistor element.

Furthermore, in the above structure, a resistance element

is connected in parallel with the diode element.

This makes possible charging through the resistor element for low charge current and through the diode element for high charge current, thus enhancing the charging efficiency regardless of the amount of charge current.

Furthermore, the switch means uses a MOS transistor. The MOS transistor is less in turning on/off power and correspondingly reduced in useless power consumption. Furthermore, the switch means can be minimized, resulting in reduction in size and weight for the electronic portable appliance.

Furthermore, the control circuit is provided with a function to intermittently operate the incorporated voltage comparator circuit and a memory circuit to memorize a last-time voltage comparison result of the voltage comparator circuit until a next operation of the voltage comparator circuit so that the switch means is controlled by the voltage comparison result memorized in the memory circuit. This allows the control circuit to operate with reduced power consumption, correspondingly reducing useless power.

Furthermore, the drive circuit has an oscillation circuit or frequency dividing circuit so that an intermittent pulse is created based on an output of the oscillation circuit or frequency dividing circuit which is required to intermittently operate the voltage comparator circuit of the control circuit. This eliminates the necessity for the control circuit to have an oscillation circuit or frequency dividing circuit to create an

intermittent pulse, correspondingly reducing power consumption in the control circuit and hence reducing useless power as stated above.

Furthermore, the power feed means has a power generating means, an oscillation circuit and a booster circuit to increase the electromotive force voltage of the power generating means by utilizing an output signal of the oscillation circuit so that an intermittent pulse is created based on an output signal of the oscillation circuit to intermittently operate the voltage comparator circuit of the control circuit. Due to this, the control circuit does not require an oscillation circuit conventionally required to create an intermittent pulse, correspondingly reducing current consumption of the control circuit and hence useless power.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a schematic block diagram of an electronic portable appliance showing Embodiment 1 of the present invention;

Fig. 2 is a schematic block diagram of an electronic portable appliance showing Embodiment 2 of the present invention;

Fig. 3 is a schematic block diagram of an electronic portable appliance showing Embodiment 3 of the present invention;

Fig. 4 is a schematic block diagram of an electronic portable appliance showing Embodiment 4 of the present invention;

Fig. 5 is a block diagram of a control circuit for the electronic portable appliance of the present invention; and

Fig 6 is a schematic block diagram showing a conventional

electronic portable appliance.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Now an electronic portable appliance according to the present invention will be described with reference to the drawings. Fig. 1 is a schematic block diagram of an electronic portable appliance according to Embodiment 1 of the invention. As shown in Fig. 1, an electronic portable appliance 100 driven on generation power comprises a power feed means 10 having a power generating means 11 and a booster circuit 12, a switch means 20, a control circuit 30, a power storing means 40 and a drive circuit 50.

sub
A8

The power feed means 10 not necessarily requires the booster circuit 12 provided that the power generating means 11 can generate an electromotive force higher than an operation voltage of the drive circuit 50 during most part of power generation. However, if not so the booster circuit 12 has to be provided. It is noted that the power generating means may be any of a scheme utilizing a coil self-induction, a solar battery cell, a thermoelectric conversion device and a piezoelectric effect, or a combination of these power generating schemes. Meanwhile, the booster circuit may be any of a switched capacitor scheme, a charge pump scheme, a scheme of rectifying and outputting alternating current amplified by a transformer and a scheme of rectifying and outputting alternating current amplified by piezoelectric element resonance, or a combination of these schemes.

sub
H1

On the other hand, the switch means 20 is provided on a power charge path for charging the power of the power feed means 10 to

Sub
P2

the power storing means 40. The control circuit 30 incorporates therein a voltage comparator circuit to compare between a terminal voltage of the switch means 20 on the side of a power feed means 10 output terminal and a terminal voltage thereof on the side of the power storing means 40. When this voltage comparator circuit detects that the terminal voltage of the switch means 20 on the power feed means is higher than the terminal voltage on the power storing means 40, the switch means 20 is tuned on to supply the power of the power feed means 10 to the power storing means 40 or the drive circuit 50. In other cases, the switch means 20 are turned off to prevent the power stored on the power storing means 40 from reversely flowing to the power feed means 10. Due to this, it is possible to realize a rectification function by the use of the switch means 20 that has conventionally been realizable only by a diode element. The switch means 20 is lower in voltage drop caused due to passing charge current as compared to that of a diode element, thus eliminating the almost all charge loss due to voltage drop. That is, the use of the switch means 20 instead of a diode element drastically improves charge efficiency. Furthermore, the switch means 20 is extremely low in the reverse current to be caused during off, i.e. corresponding to a reverse current through a diode element, as compared to a diode element. That is, there is almost no consumption of useless power in the form of reverse current. Consequently, it is possible to realize further longer time operation for an electronic portable appliance operating on generation power. Because less generation power is

Sub AH
required for a same operation time as the conventional, the power generating means can be reduced in size and weight. Due to this, the electronic portable appliance can be reduced in size and weight.

It is noted that, although the switch means 20 may be any of switch elements, the invention recommends the use of a MOS transistor. The MOS transistor, among switch elements, requires less power to turn on and off, and has a feature of a categorically smallest size. Accordingly, the use of a MOS transistor for the switch element 20 enables longer operation and size and weight reduction for the electronic portable appliance.

Sub AH
Incidentally, Fig. 1 shows the case that the switch means 20 utilizes a P channel MOS transistor. As shown in Fig. 1, the P channel MOS transistor has a source and substrate connected to the power storing means 40, a drain connected to the power feed means 10, and a gate connected to receive a control signal from the control circuit 30.

Sub AH
Furthermore, the switch means 20 has a resistance component to provide a drop voltage of approximately 20 mV, due to a current caused when charging the power of the power feed means 10 to the power storing means 40 or when the storage power on the power storing means 40 reversely flows to the power feed means 10. Due to this, even where the voltage comparator circuit of the control circuit 30 has an offset voltage to be encountered as an unavoidable problem with a voltage comparator circuit, the 20 mV drop voltage by the resistance component can absorb such offset voltage.

Accordingly, it is possible to prevent oscillation phenomenon, malfunction and so on to be caused due to the relationship between the switch means 20 and the control circuit 30. It is also possible to prevent malfunction in the control circuit 30 to be caused due to erroneous detection resulting from gain insufficiency, which is another unavoidable problem with a voltage comparator circuit of the control circuit 30. That is, because the control circuit 30 stably controls the switch means 20, the switch means 20 can realize an equivalent function to the conventional diode element. Also, the voltage to be compared by the voltage comparator circuit of the control circuit 30 may be taken at any location provided that it is on a charging path at forward and rear points of the switch element 20. Furthermore, the switch element 20 may be at any location on the charge path.

Referring to Fig. 2, there is shown a schematic block diagram of an electronic portable appliance according to Embodiment 2 of the invention. This is in almost a same structure as the schematic block diagram of the electronic portable appliance of Embodiment 1 shown in Fig. 1. In Fig. 2 an electronic portable appliance 200 to be operated on generation power is different in that a resistor element 201 with the same resistance value as the resistance component of the switch means 20 is provided, in place of the resistance component, in series with the switch means 20 on the charging path in order to reduce the resistance value of the resistance component. Furthermore, in Embodiment 2 of Fig. 2 the points to be compared in voltage by the voltage comparator

circuit of the control circuit 30 are taken by a terminal of a resistor element 201 on a power feed means 10 side and a terminal of the switch means 20 on a power storing means 40 side, although they are across the switch means 20 in Embodiment 1 of Fig. 1.

Due to this, a best resistance value can be set for stably operating the control circuit 30 in accordance with the ability of the power feed means 10 by replacing with the resistor element 201, in addition to the effect offered by the electronic portable appliance 100 of Embodiment 1 shown in Fig. 1. Thus, there obtains an effect that time and labor be omitted in designing a switch means 20 having a best resistance component for stably operating the control circuit 30 in accordance with the ability of the power feed means 10 or searching for a switch means 20 having a close resistance value to a best resistance value.

Incidentally, in Fig. 2 the points to be compared in voltage by the voltage comparator circuit of the control means 30 may be anywhere provided that they are on a charging path at forward and rear points of the resistor element 201 and switch means 20. Furthermore, the resistor element 201 may be anywhere on the charging path. Furthermore, the resistor element 201 and switch means 20 may be anywhere on the charging path.

Referring to Fig. 3, there is shown a schematic block diagram of an electronic portable appliance according to Embodiment 3 of the invention. As shown in Fig. 3, the electronic portable appliance of Embodiment 3 is different from Embodiment 2 of Fig. 2 in that a diode element 301 is provided to replace the resistor

5w
P12

Patent to S. S. S. S. S.

element 201 of the electronic portable appliance 200 of Embodiment 2 in Fig. 2. That is, the electronic portable appliance of Embodiment 3 has the diode element 301 connected to provide forward charging from the power feed means 10 to the power storing means 30.

Sub
#13
Circuit 301
Here, the diode element 301 adopts a diode element having a forward drop voltage by far lower than that of a diode element used in the conventional electronic portable appliance driven on generation power. This can suppress low a drop voltage on a charging path from the power feed means 10 to the power storing means 40 and hence improve charge efficiency, as compared to the conventional electronic portable appliance driven on generation power. Of course, the adoption of the diode element with such low forward drop voltage increases reverse current through the diode element. However, such reverse current when flowing can be put off by the switch means 20. Thus, reverse current can be suppressed by far low.

Sub
#14
Circuit 301
Furthermore, the diode element 301 has the function of producing a drop voltage to be provided by the resistance component of the switch means 20 of the electronic portable appliance shown in Fig. 1 or by the resistor element 201 of the electronic portable appliance shown in Fig. 2, thereby providing an effect of stably operating the control circuit 30. Furthermore, for high charge current, provided is an effect of improving the charge efficiency. This is because the drop voltage due to a resistance component caused upon passing the resistance component by a charge current

linearly increases with increase in the charge current. On the other hand, for low charging current the drop voltage due to a diode element is greater by an amount of a forward drop voltage than a drop voltage due to a resistance component. For high charging current, that drop voltage is lower than a drop voltage due to the resistance component. That is, in the case of high charging current, the utilization of a diode element provides higher charging efficiency than the use of a resistance component.

Incidentally, in Fig. 3 the points to be compared of voltage by the voltage comparator circuit of the control means 30 may be anywhere provided that positioned on a charging path at forward and rear points of the diode element 301 and switch means 20. Furthermore, the diode element 301 and the switch means 20 may be provided anywhere on the charging path.

Referring to Fig. 4, there is shown a schematic block diagram of an electronic portable appliance according to Embodiment 4 of the invention. The structure is almost the same as that of Embodiment 3 shown in Fig 3. The different point is that a resistor element 201 is provided in parallel with the diode element 301 as shown in Fig. 4.

This structure realizes an electronic portable appliance possessing both the effect given by the structure shown in Fig. 2 and the effect by the structure of Fig. 3. That is, for low charge current nearly all the charge current is supplied through the resistor element 201. For high charge current almost all the charge current is supplied through the diode element 301. Due

to this reason, in both the low and high charge current cases, it is possible to decrease the drop voltage upon charging thus offering efficient charging.

Incidentally, in Fig. 4 the points to be compared of voltage by the voltage comparator circuit of the control means 30 may be anywhere provided that located on a charging path at forward and rear points of the diode element 301 and resistor element 201 connected in parallel therewith. Furthermore, the diode element 301 and the resistor element 201 connected in parallel therewith or the switch means 20 may be anywhere on the charging path.

Referring to Fig. 5, there is shown a schematic block diagram of a control circuit 30 to be used in the electronic portable appliance for Embodiments 1 to 4 shown in Fig. 1 to Fig. 4. As shown in Fig. 5, a first input terminal 502 is connected to a charging path on a front stage of means for causing a drop voltage due to a charge current or to a charging path on a front stage of a switch means 20. A second input terminal 503 is connected to a charging path on a rear stage of the means for causing a drop voltage due to a charge current or to a charging path on a rear stage of the switch means 20. Furthermore, a GND connection terminal 504 is connected to a GND terminal. Also, a control circuit 30 is provided with an output terminal 501 to output a control signal to turn on and off the switch means.

The input power voltage to the first input terminal 502 is divided by a first bleeder resistor formed by a resistor 507 and a resistor 508. The input power voltage to the second input

terminal 503 is divided by a second bleeder resistor formed by a resistor 509 and a resistor 510. A voltage comparator circuit 506 compares a voltage divided by the first bleeder resistor with a voltage divided by the second bleeder resistor, and outputs a comparison result to a memory circuit 505. Furthermore, a switch means 511 is provided between the first bleeder resistor and the GND terminal. A switch means 513 is provided between the second bleeder resistor and the GND terminal. A switch means 512 is provided between the voltage comparator circuit 506 and the GND terminal. Each switch means 511, 512, 513 is intermittently turned on by an intermittent signal outputted by an intermittent pulse generating circuit 516. Also, the memory circuit 505 receives such an intermittent pulse to acknowledge timing of turning on the switch means 511, 512, 513, and memorize a result of comparison by the voltage comparator circuit 506 each time the switch means 511, 512, 513 turns on. The comparison result memorized by the memory circuit 505 is outputted to the output terminal 501, as a signal to control the switch means 20 shown in Fig. 1 to Fig. 4. Furthermore, the intermittent pulse generating circuit 516 creates an intermittent pulse based on a frequency divided signal divided of a clock signal of an oscillation circuit 514 by the frequency dividing circuit 515. It is noted that here the ratio of the resistor 507 to the resistor 508 is taken the same as the ratio of the resistor 509 to the resistor 510, in order to enhance highest the accuracy of comparison by the voltage comparator circuit 506.

The control circuit 30 configured as above makes possible intermittent operation for the voltage comparator circuit 506 with the first bleeder resistor and second bleeder resistor, hence providing current reduction for the control circuit 30.

Furthermore, where the drive circuit 50 shown in Fig. 1 to Fig. 4 incorporates an oscillation circuit and frequency dividing circuit as in a timepiece IC or a booster circuit 12 is a booster circuit incorporating an oscillation circuit of a switched capacitor scheme or the like, the oscillation circuit 514 and the frequency dividing circuit 515 shown in Fig 5 are not required. It is satisfactory that the intermittent pulse generating circuit 516 be inputted by a divided clock signal from a timepiece IC or the frequency dividing circuit 515 be inputted by a clock signal of the oscillation circuit provided in the booster circuit. Thus, it is possible to reduce the current to be consumed by the oscillation circuit 514 and frequency dividing circuit 515 or the oscillation circuit 514, hence further reducing current consumption for the control circuit 30.

According to the invention, the electronic portable appliance to be driven on generation power can efficiently charge generation power or increased generation power to the power storing means. Furthermore, it is possible to decrease other consumption than by the drive circuit of power charged on the power storing means, making possible long-time operation of the electronic portable appliance.

Also, for a same operating time of the electronic portable

appliance, it is possible to operate over a same time with a reduced amount of generation power. Accordingly, the power generating means or booster circuit can be reduced in size and weight, correspondingly reducing the size and weight of the electronic portable appliance.

Furthermore, according to the invention, where the drive circuit or booster circuit has an oscillation circuit or frequency dividing circuit, it is possible to reduce other consumption than by the drive circuit of power stored on the power storing means, further increasing the operating time of the electronic portable appliance or reducing the size and weight thereof.